



## HX 3000 C5 RCD

PORTABLE POWER

GENERATING SET Range INTENS

### PRODUCT ADVANTAGES

Inclusive differential protection  
Generating set guaranteed 3 years  
HONDA Professional Engine  
Solid and high-performance equipment

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HX 3000 C5 RCD

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	2,7
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3,1
75% cons. (l/h)	1,3
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	196
Oil system capacity including filters (l)	0,6

### ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker + Residual Current Device

### DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

### PACKAGING

Packaging type	Box
Length (cm)	60,5
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661

### ACCESSORIES SUPPLIED

Funnel  
User and maintenance manual

### OPTIONS

<b>STD-FR</b>	Compliant to NF-C15-401
<b>R05M</b>	R05M - Manual source inverter for connecting a single-phase generator to a house
<b>R06</b>	R06 - Trolley kit for HX 3000 / HXC 3000 ; Puncture-proof wheels Ø 187 mm
<b>3499231033104</b>	R18 - Maintenance kit for HX 3000 including oil, spark plug and air filter
<b>RBH1</b>	RBH1 - Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE
<b>RBH0-5</b>	RBH0-5 - Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE
<b>RHO</b>	RHO - Protective cover for HX 3000 / HXC 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm
<b>RPM</b>	RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
<b>RPQ</b>	RPQ - 1m earth spike, supplied with 2m 10mm <sup>2</sup> mains cable
<b>RKD1</b>	RKD1 - Kit of 2 removable differential adaptors for domestic sockets 16A
<b>3499231920831</b>	GSC - Generator Smart Care : Bluetooth box which can be used on all portable generator