



HX 3000 C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 3000 C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	2,7
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3,1
75% cons. (l/h)	1,3
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	196
Oil system capacity including filters (l)	0,6

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60,5
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

- R01** This set includes the hour meter and the differential circuit breaker
- R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut
- R06** Trolley kit for 2 and 3 kW generating sets
- 3499231033104** R18 - Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)
- RBH1** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
- RBH0-5** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
- RHO** Cover for KOHLER 's generating sets, welding sets and water pumps
- RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable
- RKD1** kit of two differential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral
- 3499231004555** GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics