



## HX 6000 C5

PORTABLE POWER

GENERATING SET Range INTENS

### PRODUCT ADVANTAGES

Solid and high-performance equipment  
Generating set guaranteed 3 years  
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HX 6000 C5

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	5,6
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1,1

### ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	79

### PACKAGING

Packaging type	Box
Length (cm)	78,5
Width (cm)	58
Height (cm)	59,5
Weight (kg)	81,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	499

### ACCESSORIES SUPPLIED

Funnel  
User and maintenance manual

### OPTIONS

- R02** This set includes the hour meter and the differential circuit breaker
- R05M** R05M - Manual source inverter for connecting a single-phase generator to a house
- RKB2** RKB2 - Trolley kit for HX 4000 - 6000 – 7500T / HXC 4000 - 6000 – 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm
- 3499231033203** R19 - Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter
- RH1** RH1 - Protective cover for HX 4000 – 6000 – 7500T / HXC 4000 – 6000 – 7500T / PERFORM 4500 – 4500 XL – 5500T – 5500 T XL – 6500 – 6500 XL – 7500 T – 7500 XL / TECHNIC 6500 – 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm
- RPM** RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
- RPQ** RPQ - 1m earth spike, supplied with 2m 10mm<sup>2</sup> mains cable
- 3499231920831** GSC - Generator Smart Care : Bluetooth box which can be used on all portable generator