



PERFORM 6500 XL C5

PORTABLE POWER

GENERATING SET Range PERFORM XL

PRODUCT ADVANTAGES

- Generating set guaranteed 3 years
- KOHLER air-cooled industrial engine
- Large Autonomy
- Good value for money
- Starting up facilitated thanks to the summer/winter positions

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime
STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range PERFORM XL

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



PERFORM 6500 XL C5

GENERAL SPECIFICATIONS

Range	PERFORM XL
Frequency (Hz)	50 Hz
Max power (kW) *	6,30
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	18
75% cons. (l/h) *	2,60
75% Autonomy (h) *	6,90
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH440_C5
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	429
Oil system capacity including filters (l)	1,30

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55,50
Height (cm)	59
Dry Weight (kg)	87

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56,50
Height (cm)	60
Weight (kg)	89
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	544

KOHLER®

SDMO®

PERFORM 6500 XL C5

ACCESSORIES SUPPLIED



Funnel



Floor maintaining slot



User and maintenance manual



Ergonomic handle grip

OPTIONS



R02

This set includes the hour meter and the differential circuit breaker.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB1HD

Trolley kit for the generating sets of 6kW or below



RKS2

Maintenance kit for KOHLER CH395 and CH440 engines.



RH1

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.

KOHLER®

SDMO®

23/07/2021

PERFORM 6500 XL C5 - PORTABLE POWER - GENERATING SET PERFORM XL

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervem - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com