



HX 3000 TB UK C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

Solid and high-performance equipment
Generating set guaranteed 3 years
HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 3000 TB UK C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	2,7
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3,1
75% cons. (l/h)	1,3
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	196
Oil system capacity including filters (l)	0,6

ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 115V 16A sockets - circuit breaker + 1 socket 230V 16A - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60,5
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661

ACCESSORIES SUPPLIED

Funnel
User and maintenance manual

OPTIONS

R06	Trolley kit for 2 and 3 kW generating sets
3499231033104	R18 - Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)
R50	16A blue 230V male plug - Sold per 1 or 10
R51	16A yellow 115V male plug - Sold per 1 or 10
R54	Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3
R55	ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3
R56	ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3
RBH1	Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
RBH0-5	Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
RHO	Cover for KOHLER 's generating sets, welding sets and water pumps
RPQ	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm ² cable
3499231004555	GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics