



### VX 200/4 UK C5

PORTABLE POWER

WELDING SET Range WELDARC INTENS

#### PRODUCT ADVANTAGES

- HONDA Professional Engine
- Generating set guaranteed 3 years
- Light storage box integrated
- Solid and high-performance equipment
- Auxiliary Single phase output

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

#### Range WELDARC INTENS

Welding sets which can be used on sites where there is no electricity.



#### GENERAL SPECIFICATIONS

Range	WELDARC INTENS
Frequency (Hz)	50 Hz
Max power (kW)	4
Max power (kVA)	4
Normal duty cycle 35% (A)	200
Intensif duty cycle 60% (A)	170
Stricking volts (V)	75
Rods diameter mini (mm)	1.6
Rods diameter maxi (mm)	4
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

#### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1,1

#### ALTERNATOR SPECIFICATION

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

#### PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 230V 16A socket - circuit breaker

#### DIMENSIONS AND WEIGHT

Length (cm)	87
Width (cm)	57
Height (cm)	55,5
Dry Weight (kg)	87

#### PACKAGING

Packaging type	Box / Pallet
Length (cm)	88
Width (cm)	58,5
Height (cm)	70
Weight (kg)	100
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0

### ACCESSORIES SUPPLIED

Storage box  
User and maintenance manual

### OPTIONS

- RKB2** Trolley kit for the generating sets superior to 6kW
- R10** Welding kit includes 2 x 5 m of cable, 1 earth clip, 1 electrode holder, 1 hammer, 1 brush and 1 mask
- R10BAC** Set of 2 x 5 m welding leads sold separately
- 3499231033203** R19 - Maintenance kit for Honda GX390 engines (except Alizé 6000E and Alizé 7500 TE)
- R50** 16A blue 230V male plug - Sold per 1 or 10
- R51** 16A yellow 115V male plug - Sold per 1 or 10
- R54** Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3
- R55** ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3
- R56** ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3
- RBH1** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
- RBH0-5** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
- RH2** Cover for SDMO 's generating sets, welding sets and water pumps
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable
- 3499231004555** GSC - GENERATOR SMART CARE, the Bluetooth module for monitoring the maintenance of generators, maintenance and diagnostics